


## TDA7222A TDA7222AD

## 3V AM/FM ONE-CHIP RADIO

#### **ADVANCE DATA**


- BUILT-IN FM F/E, AM/FM IF AND FM MPX
- AM DETECTOR COIL AND IF COUPLING CA-PACITOR ARE NOT NEEDED
- COMPACT PACKAGE: 24-Pin Shrink
- OPERATING SUPPLY VOLTAGE RANGE V<sub>CC</sub> (opr) = 1.8 to 7.0V (T<sub>A</sub> = 25°C)
- LED DRIVE CIRCUIT FOR TUNING INDICA-TION



## **DESCRIPTION**


TDA7222A and TDA7222AD are AM/FM chip tuner ICs, which are designed for portable radios and 3V headphone radios.

## **PIN CONNECTIONS**



February 1995 1/7

## **BLOCK DIAGRAM**



7222A-02.EPS

## **ABSOLUTE MAXIMUM RATINGS**

| Symbol            | Parameter             | Value     | Unit |
|-------------------|-----------------------|-----------|------|
| Vs                | Supply Voltage        | 9         | V    |
| I <sub>LED</sub>  | LED Current           | 10        | mA   |
| V <sub>LED</sub>  | LED Voltage           | 10        | V    |
| T <sub>oper</sub> | Operating Temperature | -20, +70  | °C   |
| T <sub>stg</sub>  | Storage Temperature   | -55, +150 | °C   |

## **RECOMMENDED OPERATING CONDITIONS**

| Symbol            | Parameter             | Value    | Unit | ] <u>a</u> |
|-------------------|-----------------------|----------|------|------------|
| Vs                | Supply Voltage        | 1.8 to 7 | V    | 100        |
| T <sub>oper</sub> | Operating Temperature | 0, +70   | °C   | 10001      |

## **ELECTRICAL CHARACTERISTICS** (unless otherwise specified)

 $T_A = 25^{\circ}C$ ,  $V_{CC} = 3V$  F/E : f = 83MHz,  $f_m = 1kHz$ 

 $\begin{array}{ll} FM\ IF & : f=10.7MHz, \Delta f=\pm\ 22.5kHz, f_m=1kHz \\ AM & : f=1MHz, MOD=30\%, f_m=1kHz \end{array}$ 

MPX:  $f_m = 1kHz$ 

| Symbol                           |                            | Parameter  | Test Conditions  | Min. | Тур.           | Max. | Unit              |
|----------------------------------|----------------------------|--|--|------|----------------|------|-------------------|
| I <sub>CC</sub> (FM)             | Sunnh                      | / Current  | V <sub>IN</sub> = 0, FM mode   |      | 13.2           | 20   | mA                |
| I <sub>CC</sub> (AM)             | Supply                     | Current  | V <sub>IN</sub> = 0, AM mode   |      | 8.4            | 13.5 | mA                |
| V <sub>IN</sub> (lim)            | F/E Input Limiting Voltage |  | - 3dB limiting   |      | 10.0           |      | dBμ               |
| Vosc                             | /                          | Local OSC Voltage  | $f_{OSC} = 72.3MHz$  |      | 105            |      | mV <sub>RMS</sub> |
| V <sub>IN</sub> (lim) IF         |                            | Input Limiting Voltage   | - 3dB limiting   | 40   | 46             | 53   | dΒμ               |
| VOD                              |                            | Recovered Output Voltage   | $V_{IN} = 80 dB\mu$  | 55   | 80             | 110  | mVкмs             |
| S/N                              | FΜ                         | Signal to Noise Ratio  | $V_{IN} = 80 dB\mu$  |      | 70             |      | dB                |
| THD                              | IF                         | Total Harmonic Distortion  | $V_{IN} = 80 dB\mu$  |      | 0.4            |      | %                 |
| AMR                              |                            | AM Rejection Ratio   | $V_{IN} = 80 dB\mu$  |      | 32             |      | dB                |
| V <sub>L</sub>                   |                            | Lamp ON Sensitivity  | I <sub>L</sub> = 1mA   | 45   | 51             | 56   | dΒμ               |
| G <sub>V</sub>                   |                            | Gain   | $V_{IN} = 26dB\mu$   | 40   | 70             | 110  | mV <sub>RMS</sub> |
| VOD                              | 1                          | Recovered Output Voltage   | $V_{IN} = 60 dB\mu$  | 55   | 80             | 110  | mV <sub>RMS</sub> |
| S/N                              | AM                         | Signal to Noise Ratio  | $V_{IN} = 60 dB\mu$  |      | 42             |      | dB                |
| THD                              |                            | Total Harmonic Distortion  | $V_{IN} = 60 dB\mu$  |      | 1.0            |      | %                 |
| V <sub>L</sub>                   |                            | Lamp ON Sensitivity  | I <sub>L</sub> = 1mA   | 20   | 25             | 30   | dΒμ               |
| R19                              | Pin 19                     | Output Resistance  | FM mode<br>AM mode   |      | 0.75<br>12.75  |      | kΩ<br>kΩ          |
| R <sub>IN</sub>                  |                            | Input Resistance   |  |      | 24             |      | kΩ                |
| R <sub>OUT</sub>                 |                            | Output Resistance  |  |      | 5              |      | kΩ                |
| V <sub>IN (Max.)</sub><br>Stereo |                            | Max. Composite Signal Input Voltage  | L + R = 90%, P = 10%<br>f <sub>m</sub> = 1kHz, THD = 3%                      |      | 350            |      | mV <sub>RMS</sub> |
| Sep                              | MPX                        | $ \begin{array}{c} f_m = 100 Hz \\ \text{Separation} & f_m = 1 \text{kHz} \\ f_m = 10 \text{kHz} \end{array} $ | $L + R = 135 \text{mV}_{\text{RMS}}$ $P = 15 \text{mV}_{\text{RMS}}$         | 25   | 32<br>32<br>32 |      | dB<br>dB<br>dB    |
| THD<br>Monaural                  |                            | Total Harmonic Distortion (monaural)   | $V_{IN} = 150 \text{mV}_{RMS}$   |      | 0.2            |      | %                 |
| THD<br>Stereo                    |                            | Total Harmonic Distortion (stereo)   | $\begin{array}{c} L+R=135\text{mV}_{RMS} \\ P=15\text{mV}_{RMS} \end{array}$ |      | 0.2            |      | %                 |
| G <sub>√</sub> (MPX)             |                            | Voltage Gain   | $V_{IN} = 150 \text{mV}_{RMS}$   | -5   | - 3            | - 1  | dB                |
| C.B.                             |                            | Channel Balance  | $V_{IN} = 150 \text{mV}_{RMS}$   | - 2  | 0              | 2    | dB                |

222A-03 TRI



## **ELECTRICAL CHARACTERISTICS** (unless otherwise specified) (continued)

 $T_A = 25^{\circ}C$ ,  $V_{CC} = 3V$  F/E : f = 83MHz,  $f_m = 1kHz$ 

 $\begin{array}{ll} FM\ IF & : f=10.7MHz, \Delta f=\pm\ 22.5kHz, f_m=1kHz\\ AM & : f=1MHz,\ MOD=30\%,\ f_m=1kHz \end{array}$ 


MPX:  $f_m = 1kHz$ 

| Symbol               |     | Parameter                     | Test Conditions  | Min. | Тур. | Max. | Unit              |
|----------------------|-----|-------------------------------|------------------|------|------|------|-------------------|
| V <sub>L</sub> (ON)  |     | Stereo Lamp (ON) Sensitivity  | Pilot Input      | 2    | 6    |      | mV <sub>RMS</sub> |
| V <sub>L</sub> (OFF) |     | Stereo Lamp (OFF) Sensitivity | Filot Iriput     |      | 2    |      | mV <sub>RMS</sub> |
| VH                   | MPX | Stereo Lamp Hysteresis        |                  |      | 3    |      | mV <sub>RMS</sub> |
| C.R.                 |     | Capture Range                 | $P = 15mV_{RMS}$ |      | ± 3  |      | %                 |
| S/N                  |     | Signal to Noise Ratio         |                  |      | 70   |      | dB                |

## **COIL DATA**


| Coil           |        | f     | L           | Со   | Qo  | Turns |       |       |                | Wire  | Ref. *     |                   |
|----------------|--------|-------|-------------|------|-----|-------|-------|-------|----------------|-------|------------|-------------------|
| N°             |        | (Hz)  | <b>(μH)</b> | (pF) | ÿ   | 1 - 2 | 2 - 3 | 1 - 3 | 1-4            | 4 - 6 | Wile       | iver.             |
| L <sub>1</sub> | FM RF  | 100M  |             |      | 100 |       |       |       | $2\frac{1}{2}$ |       | 0.5∅ UEW   | S -53T-037-202    |
| L <sub>2</sub> | FM OSC | 100M  |             |      | 100 |       |       | 2 3/4 |                |       | 0.5∅ UEW   | S - 0258-24       |
| L <sub>3</sub> | AM OSC | 796k  | 238         |      | 115 | 13    | 73    |       |                |       | 0.08Ø UEW  | S - 4147-1356-038 |
| T <sub>1</sub> | FM MIX | 10.7M |             | 75   | 100 |       |       | 13    |                | 2     | 0.1Ø UEW   | S - 2153-414-041  |
| T <sub>2</sub> | AM MIX | 455k  |             | 180  | 120 |       |       | 180   |                | 15    | 0.08Ø UEW  | S - 2150-2162-165 |
| T <sub>3</sub> | FM DET | 10.7M |             | 47   | 165 |       |       | 16    |                |       | 0.09∅ MUEW | S - 2153-4095-122 |

<sup>\*</sup> S: Sumida Electric CO, LTD.




7222A-05.TBL

## **APPLICATION CIRCUIT**




# **PACKAGE MECHANICAL DATA** (TDA7222A) 24 PINS - PLASTIC SHRINK DIP



| Dimensions |      | Millimeters |       |       | Inches |       |  |  |
|------------|------|-------------|-------|-------|--------|-------|--|--|
| Dimensions | Min. | Тур.        | Max.  | Min.  | Тур.   | Max.  |  |  |
| Α          |      | 3.3         |       |       | 0.130  |       |  |  |
| a1         | 0.51 |             |       | 0.020 |        |       |  |  |
| b          | 0.35 |             | 0.59  | 0.014 |        | 0.023 |  |  |
| b1         | 0.2  |             | 0.36  | 0.008 |        | 0.014 |  |  |
| b2         | 0.75 |             | 1.42  | 0.030 |        | 0.056 |  |  |
| b3         | 0.75 |             |       | 0.030 |        |       |  |  |
| D          |      |             | 23.11 |       |        | 0.910 |  |  |
| E          | 7.95 |             | 9.73  | 0.313 |        | 0.383 |  |  |
| е          |      | 1.778       |       |       | 0.070  |       |  |  |
| e3         |      | 19.558      |       |       | 0.770  |       |  |  |
| e4         |      | 7.62        |       |       | 0.300  |       |  |  |
| F          |      |             | 6.86  |       |        | 0270  |  |  |
| i          |      |             | 5.08  |       |        | 0.200 |  |  |
| L          | 2.54 |             |       | 0.100 |        |       |  |  |

## PACKAGE MECHANICAL DATA (TDA7222AD)

28 PINS - PLASTIC MICROPACKAGE (SO)



| Dimensions |      | Millimeters |       | Inches |       |       |  |  |
|------------|------|-------------|-------|--------|-------|-------|--|--|
| Dimensions | Min. | Тур.        | Max.  | Min.   | Тур.  | Max.  |  |  |
| Α          |      |             | 2.65  |        |       | 0.104 |  |  |
| a1         | 0.1  |             | 0.3   | 0.004  |       | 0.012 |  |  |
| b          | 0.35 |             | 0.49  | 0.014  |       | 0.019 |  |  |
| b1         | 0.23 |             | 0.32  | 0.009  |       | 0.013 |  |  |
| С          |      | 0.5         |       |        | 0.020 |       |  |  |
| c1         |      |             | 45°   | (typ.) | •     |       |  |  |
| D          | 17.7 |             | 18.1  | 0.697  |       | 0.713 |  |  |
| Е          | 10   |             | 10.65 | 0.394  |       | 0.419 |  |  |
| е          |      | 1.27        |       |        | 0.050 |       |  |  |
| e3         |      | 16.51       |       |        | 0.65  |       |  |  |
| F          | 7.4  |             | 7.6   | 0.291  |       | 0.299 |  |  |
| L          | 0.4  |             | 1.27  | 0.016  |       | 0.050 |  |  |
| S          |      |             | 8° (ı | max.)  |       |       |  |  |

Information furnished is believed to be accurate and reliable. However, SGS-THOMSON Microelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No licence is granted by implication or otherwise under any patent or patent rights of SGS-THOMSON Microelectronics. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. SGS-THOMSON Microelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of SGS-THOMSON Microelectronics.

#### © 1995 SGS-THOMSON Microelectronics - All Rights Reserved

Purchase of I<sup>2</sup>C Components of SGS-THOMSON Microelectronics, conveys a license under the Philips I<sup>2</sup>C Patent. Rights to use these components in a I<sup>2</sup>C system, is granted provided that the system conforms to the I<sup>2</sup>C Standard Specifications as defined by Philips.

### SGS-THOMSON Microelectronics GROUP OF COMPANIES

Australia - Brazil - China - France - Germany - Hong Kong - Italy - Japan - Korea - Malaysia - Malta - Morocco The Netherlands - Singapore - Spain - Sweden - Switzerland - Taiwan - Thailand - United Kingdom - U.S.A.

